

## CUTTING TOOL V55G-AS-P

Part no: 72103000



#### **FORCE**

80 kN

### **PERFORMANCE WITH 5.0 AH BATTERY**

approx. 100 cycles

### **FEATURES**

- Guillotine closed cutting head with bolt lock for secure operation.
- Reliable cutting of cables, overhead conductors, and solid materials.
- Ergonomic design optimised for overhead work.

### **APPLICATION**

Cutting of power and underground cables, overhead utility lines as well as round material.

#### **SPECIFICATIONS**

Material / Conductor size and Diameter	Aluminum				
	Cutting (class 1, 2)	up to Ø 57 mm (max. 4x240 mm² se)			
	ACSR	up to Ø 46 mm (max. 570-640 mm²)			
	Aldrey (AL3)	up to Ø 46 mm (max. 760 mm²)			
	Round material	up to Ø 28 mm			
	Copper				
	Cutting (class 1, 2)	up to Ø 53 mm (max. 4x185/95 mm² sm)			
	Round material	up to Ø 35 mm			
	Steel				
	Wire rope	6x7: up to Ø 20 mm, 6x12 / 6x19: up to Ø 30 mm			
	Reinforcing Rod	up to Ø 20 mm			
Force	80 kN				
Opening Width	55 mm				
Battery Voltage	18 V (compatible with Makita)				
Weight	9.1 kg				
Dimensions* L x B x H	537 x 80 x 388 mm				
Cutting Head	Guillotine closed, 360° rotable				
Shape	Pistol grip				

<sup>\*</sup> Supplied in a lightweight plastic case (battery and charger not included).



# CUTTING TOOL V55G-AS-P

Part no: 72103000

### **INDUSTRIES**

Energy suppliers, grid operators, overhead utility line contruction, electrical engineering, solar technology

#### **ACCESSORIES**

Item	Туре	Description		Part no.
Li-ion Battery Makita 18 V*	BL1850B	Capacity: Weight: Charger: Charging time:	5.0 Ah 0.64 kg DC18RC 45 min (100 %)	79300115
Quick charger	DC18RC	Voltage: Frequency: Output voltage: Weight: Dimension (mm):	220 – 240 V 50 – 60 Hz 8 V 0.9 kg 156 x 190 x 84	79300120
Battery adapter BO	ADAP-BO-18V	Adapter compatible with Bosch (18V)		79300092
Battery adapter MI	ADAP-MI-18V	Adapter compatible with Milwaukee (18V)		79300093
Battery adapter DE	ADAP-DE-18V	Adapter compatible with Dewalt (18V)		79300094

<sup>\*</sup> Additionally, 18V Makita batteries can be used: BL1815N, BL1820B, BL1830B, BL1840B, BL1860B.