

## CRIMPING TOOL VB400-AP-P-DID

Part no: 76001000



### FORCE

120 kN

### PERFORMANCE WITH 5.0 AH BATTERY

approx. 100 cycles

### FEATURES

- Deep-Indent-Crimping (DID) - compatible with all standard DID press inserts.
- Also suitable for wide crimping – adapter for C dies included in delivery
- Auto-release function.

## APPLICATION

DID crimping of compression cable lugs (DIN 46235 / DIN 46329) and connectors, additionally hexagonal crimping of tubular lugs and solderless terminals as well as connectors.

## SPECIFICATIONS

<b>Material / Conductor size and Diameter</b>	<b>Aluminium</b>	
	Crimping (DID)	25–240 mm <sup>2</sup> (DIN)
	Crimping (Adapter / C dies)	6–300 mm <sup>2</sup> (DIN)
	Crimping (Adapter / C dies)	6–400 mm <sup>2</sup> (NON-DIN)
	<b>Copper</b>	
	Crimping (DID)	25–240 mm <sup>2</sup> (DIN)
	Crimping (Adapter / C dies)	10–300 mm <sup>2</sup> (DIN / NON-DIN)
<b>Force</b>	120 kN	
<b>Crimping cycle</b>	5–8 s (depending on crimping cross-section)	
<b>Stroke</b>	17 mm	
<b>Battery Voltage</b>	18 V (compatible with Makita)	
<b>Weight</b>	6,3 kg	
<b>Dimensions* L x B x H</b>	405 x 80 x 305 mm	
<b>Cutting Head</b>	Closed, rotatable, flip top opening	
<b>Shape</b>	pistol grip	

\* Supplied in a lightweight plastic case (crimping dies, battery and charger not included).

**SHOP ONLINE NOW: [SELECTED-TOOLS.DE](https://www.selected-tools.de)**

Vitolon | P +49 40 511 28-299 | E [info@vitolon.com](mailto:info@vitolon.com) | [vitolon.com](https://www.vitolon.com)

**INDUSTRIES**

Energy suppliers, wind energy, plant construction, grid operators

**ACCESSORIES**

Item	Type	Description	Part no.
<b>Li-ion Battery Makita 18 V*</b>	BL1850B	Capacity: Weight: Charger: Charging time:	5.0 Ah 0.64 kg DC18RC 45 min (100 %) 79300115
<b>Quick charger</b>	DC18RC	Voltage: Frequency: Output voltage: Weight: Dimension (mm):	220 – 240 V 50 – 60 Hz 8 V 0,9 kg 156 x 190 x 84 79300120
<b>Battery adapter BO</b>	ADAP-BO-18V	Adapter compatible with Bosch (18V)	79300092
<b>Battery adapter MI</b>	ADAP-MI-18V	Adapter compatible with Milwaukee (18V)	79300093
<b>Battery adapter DE</b>	ADAP-DE-18V	Adapter compatible with Dewalt (18V)	79300094

\* Additionally, 18V Makita batteries can be used: BL1815N, BL1820B, BL1830B, BL1840B, BL1860B.